


FM EO2-Functional nut

for steel tubes




Series	D1 	T1	L1	S1	Order code				Weight g/1 piece
					FM...CF Steel + Sealing		FM...VITCF Steel + Sealing		
					Sealing NBR	PN (bar)	Sealing FKM	PN (bar)	
LL	04	M 08x1.0	11.0	10	FM04LLCF	100	—	100	5
	06	M 10x1.0	11.5	12	—	—	—	—	6
L	06	M 12x1.5	14.5	14	FM06LCF	500	FM06LVITCF	500	12
	08	M 14x1.5	14.5	17	FM08LCF	500	FM08LVITCF	500	17
	10	M 16x1.5	15.5	19	FM10LCF	500	FM10LVITCF	500	22
	12	M 18x1.5	15.5	22	FM12LCF	400	FM12LVITCF	400	30
	15	M 22x1.5	17.0	27	FM15LCF	400	FM15LVITCF	400	48
	18	M 26x1.5	18.0	32	FM18LCF	400	FM18LVITCF	400	70
	22	M 30x2.0	20.0	36	FM22LCF	250	FM22LVITCF	250	94
	28	M 36x2.0	21.0	41	FM28LCF	250	FM28LVITCF	250	106
	35	M 45x2.0	24.0	50	FM35LCF	250	FM35LVITCF	250	160
	42	M 52x2.0	24.0	60	FM42LCF	250	FM42LVITCF	250	244
S	06	M 14x1.5	16.5	17	FM06SCF	800	FM06SVITCF	800	20
	08	M 16x1.5	16.5	19	FM08SCF	800	FM08SVITCF	800	23
	10	M 18x1.5	17.5	22	FM10SCF	800	FM10SVITCF	800	37
	12	M 20x1.5	17.5	24	FM12SCF	630	FM12SVITCF	630	39
	16	M 24x1.5	20.5	30	FM16SCF	630	FM16SVITCF	630	72
	20	M 30x2.0	24.0	36	FM20SCF	420	FM20SVITCF	420	121
	25	M 36x2.0	27.0	46	FM25SCF	420	FM25SVITCF	420	221
	30	M 42x2.0	29.0	50	FM30SCF	420	FM30SVITCF	420	248
38	M 52x2.0	32.5	60	FM38SCF	420	FM38SVITCF	420	367	

$$\frac{PN \text{ (bar)}}{10} = PN \text{ (MPa)}$$

FM EO2-Functional nut

for stainless steel tubes



Series	D1 	T1	L1	S1	Order code								Weight g/1 piece	
					FM...71 Stainless Steel		FM...NBR71 Stainless Steel		FM...SSA Steel + Sealing Retaining ring: Stainless Steel		FM...VITSSA Steel + Sealing Retaining ring: Stainless Steel			
					Sealing FKM	PN (bar)	Sealing NBR	PN (bar)	Sealing NBR	PN (bar)	Sealing FKM	PN (bar)		
LL	04	M 08×1.0	11.0	10	—	—	—	—	FM04LLSSA	100	—	—	5	
	06	M 10×1.0	11.5	12	—	—	—	—	FM06LLSSA	100	—	—	6	
L	06	M 12×1.5	14.5	14	FM06L71	315	FM06LNBR71	315	FM06LSSA	315	FM06LVITSSA	315	12	
	08	M 14×1.5	14.5	17	FM08L71	315	FM08LNBR71	315	FM08LSSA	315	FM08LVITSSA	315	17	
	10	M 16×1.5	15.5	19	FM10L71	315	FM10LNBR71	315	FM10LSSA	315	FM10LVITSSA	315	22	
	12	M 18×1.5	15.5	22	FM12L71	315	FM12LNBR71	315	FM12LSSA	315	FM12LVITSSA	315	30	
	15	M 22×1.5	17.0	27	FM15L71	315	FM15LNBR71	315	FM15LSSA	315	FM15LVITSSA	315	48	
	18	M 26×1.5	18.0	32	FM18L71	315	FM18LNBR71	315	FM18LSSA	315	FM18LVITSSA	315	70	
	22	M 30×2.0	20.0	36	FM22L71	160	FM22LNBR71	160	FM22LSSA	160	FM22LVITSSA	160	94	
	28	M 36×2.0	21.0	41	FM28L71	160	FM28LNBR71	160	FM28LSSA	160	FM28LVITSSA	160	106	
	35	M 45×2.0	24.0	50	FM35L71	160	FM35LNBR71	160	FM35LSSA	160	FM35LVITSSA	160	160	
	42	M 52×2.0	24.0	60	FM42L71	160	FM42LNBR71	160	FM42LSSA	160	FM42LVITSSA	160	244	
	S	06	M 14×1.5	16.5	17	FM06S71	630	FM06SNBR71	630	FM06SSSA	630	FM06SVITSSA	630	20
		08	M 16×1.5	16.5	19	FM08S71	630	FM08SNBR71	630	FM08SSSA	630	FM08SVITSSA	630	23
10		M 18×1.5	17.5	22	FM10S71	630	FM10SNBR71	630	FM10SSSA	630	FM10SVITSSA	630	37	
12		M 20×1.5	17.5	24	FM12S71	630	FM12SNBR71	630	FM12SSSA	630	FM12SVITSSA	630	39	
16		M 24×1.5	20.5	30	FM16S71	400	FM16SNBR71	400	FM16SSSA	400	FM16SVITSSA	400	72	
20		M 30×2.0	24.0	36	FM20S71	400	FM20SNBR71	400	FM20SSSA	400	FM20SVITSSA	400	121	
25		M 36×2.0	27.0	46	FM25S71	400	FM25SNBR71	400	FM25SSSA	400	FM25SVITSSA	400	221	
30		M 42×2.0	29.0	50	FM30S71	400	FM30SNBR71	400	FM30SSSA	400	FM30SVITSSA	400	248	
38		M 52×2.0	32.5	60	FM38S71	315	FM38SNBR71	315	FM38SSSA	315	FM38SVITSSA	315	367	

$$\frac{\text{PN (bar)}}{10} = \text{PN (MPa)}$$